

Quantec Corridor Display (no controls)

Part No. QT608CD



Overview

- A 16 character x 2 line display used to indicate incoming calls in corridors, staff rooms, nursing stations, etc.
- Shows call type, call location and (depending on the device used to make the call) the User ID or name of the person calling.
- Highest priority calls are shown first with a message saying how many calls are waiting.
- Flash and sounder rates intensify to reflect the urgency of incoming calls.
- Adjustable contrast and volume controls.
- External sounder connection.



More Information

Technical Specifications

Power requirements	Nominal 24V DC (from Quantec Controller/Network)
Quiescent current	5mA (with back light off).
Indicators	2 line x 16 character backlit LCD display.
Controls	None. If controls are required use a QT608C display.
Connections	Net +: Net -
Expansion connections	External sounder connection (current sink to the NET- line rated at 30 V, 30mA, 300 mW dissipation max.)



Onboard Sounder	Yes.
Onboard Infrared Receiver	No.
Product dimensions (mm)	147 W x 87 H x 35 D mm. Mount on a 35mm deep back box.
Construction & finish	Plastic.
IP Rating	IP41.
Weight	166g.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom