

Quantec Display Interface

Part No. OP915



Overview

- Allows a QT608CD1S large corridor display to be connected to a Quantec-Pro call system via an RS232 serial interface lead (supplied with the large display).
- Mounts on a standard UK 20mm double gang flush or surface back box.
- The data connection to the large display is monitored. If this is disconnected or the large display is switched off then the QT615S appears as "Missing" on the Quantec controller



More Information

Technical Specifications

Power requirements Nominal 24V DC (from Quantec Controller/Network)

Less than 5mA. Quiescent current

Indicators None.

Controls None. If controls are required use a QT608C display.

Connections Net +: Net -; RS232 serial port.

Product dimensions (mm) $147~\mathrm{W}~x~86~\mathrm{H}~x~23~\mathrm{D}$ mm. Mount on a 35mm deep double gang back box.

Construction & finish Plastic.



T 01942 322744

E sales@c-tec.co.uk

W www.c-tec.com

















F 01942 829867



IP Rating IP41. Weight 260g.

Operating conditions/temperature -5°C to +40°C. Max relative humidity: 95%.















